

DARE TO DREAM

ENERTECH DEVICES

DIGITAL AMMETERS



- ✓ Input Current : 5.00 A AC Max
- ✓ Auxilliary Supply : 230 VAC +/- 10 %
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Amp
- ✓ CT ratio settable upto 1000/5 A
- ✓ Enclosure : ABS Plastic
- ✓ Size : 96 X 96 X 65 mm
- ✓ Panel Cutout : 90 X 90 mm

- ✓ Input Current : 5.00 A AC Max
- ✓ Auxilliary Supply : 230 VAC +/- 10%
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Amp
- ✓ CT ratio settable upto 1000/5A
- ✓ Enclosure : ABS Plastic
- ✓ Size : 48 X 96 X 110 mm
- ✓ Panel Cutout : 46 X 92 mm



- ✓ Input Current : 5.00 A AC Max
- ✓ Auxilliary Supply : 230 VAC +/- 10 %
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Amps
- ✓ CT ratio settable upto 1000/5A
- ✓ Enclosure : ABS Plastic
- ✓ Size : 72 X 72 X 65 mm
- ✓ Panel Cutout : 68 X 68 mm

- ✓ Input Current : 3 phase R,Y,B
- ✓ Auxilliary Supply : 230 VAC +/- 10 %
- ✓ Display R Y B Currents
- ✓ Auto Scanning
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Volt
- ✓ CT ratio settable upto 3000/5A
- ✓ Enclosure : ABS Plastic
- ✓ Size : 96 X 96 X 65 mm
- ✓ Panel Cutout : 92 X 92 mm



Ordering Information

Code no	Description
A1-96	Digital Ammeter, Size 96X96X65, Range Max 999 Amps CT operated
A1-72	Digital Ammeter, Size 72X72X65, Range Max 999 Amps CT operated
A1-48	Digital Ammeter, Size 48X96X65, Range Max 999 Amps CT operated
A3-96	Three Phase Digital Ammeter, Size 96X96X65, Range Max 3000 Amps