

DARE TO DREAM

ENERTECH DEVICES

Digital Voltmeters

- ✓ Input Voltage : 230 VAC / 500 VAC
- ✓ Auxilliary Supply : 230 V +/- 10 %
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Volt
- ✓ Enclosure : ABS Plastic
- ✓ Size : 96 X 96 X 65 mm
- ✓ Panel Cutout : 90 X 90 mm



- ✓ Input Voltage : 230 VAC / 500 VAC
- ✓ Auxilliary Supply : 230 V +/- 10 %
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Volt
- ✓ Enclosure : ABS Plastic
- ✓ Size : 48 X 96 X 110 mm
- ✓ Panel Cutout : 46 X 92 mm



- ✓ Input Voltage : 230 VAC / 500 VAC
- ✓ Auxilliary Supply : 230 V +/- 10 %
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Volt
- ✓ Enclosure : ABS Plastic
- ✓ Size : 72 X 72 X 65 mm
- ✓ Panel Cutout : 69 X 69 mm

- ✓ Input Voltage : 3 phase R,Y,B,N
- ✓ Auxilliary Supply : Between R-N
- ✓ Display RN, YN, BN, RY, YB, BR Voltages
- ✓ Auto Scanning
- ✓ Accuracy : +/- 1 %
- ✓ Resolution : 1 Volt
- ✓ Enclosure : ABS Plastic
- ✓ Size : 96 X 96 X 65 mm
- ✓ Panel Cutout : 90 X 90 mm



Ordering Information

Code no	Description
V1-96	Digital Voltmeter, Size 96X96X65, Range Max 300 V
V1-72	Digital Voltmeter, Size 72X72X65, Range Max 300 V
V1-48	Digital Voltmeter, Size 48X96X65, Range Max 300 V
V2-96	Digital Voltmeter, Size 96X96X65, Range Max 500 V
V2-72	Digital Voltmeter, Size 72X72X65, Range Max 300 V
V2-48	Digital Voltmeter, Size 48X96X65, Range Max 500 V
V3-96	Three Phase Digital Voltmeter, Size 96X96X65, Range Max 500 V